



Description:

The RDL HD-PA35U 35 Watt Power Amplifier is equipped with a single unbalanced stereo summing input for connecting a background music source. This amplifier includes an analog compressor/limiter allowing it to produce clear audio output levels that normally require an amplifier with a much higher output power rating. The HD-PA35U shuts down (standby "sleep" mode) when audio is absent and automatically turns on when needed. In this application, an RDL RLC10K Remote Level Control is provided to adjust the output level of the amplifier. This remote control is designed to be mounted in a standard US single gang electrical box (or RDL WB-1U Universal Wall Box for international installations) with an RDL CP-1 Cover Plate. Bass and Treble tone controls are provided on the amplifier front panel.

Parts List

Product	QTY
CP-1	1
HD-PA35U	1
RLC10K	1

Recommended Pwr. Supplies

Product	QTY
HD-MA35U Power Supply	1, Included

Line Color Key

Red	Line Level Audio Signal
Brown	Loudspeaker Level
Purple	Control Signal
Yellow	Video
Blue	Mic Level Audio Signal
Green	Ground
Brown	Power
Orange	Miscellaneous